

Agilent E8267D PSG Vector Signal Generator

Data Sheet



The Agilent E8267D is a fully synthesized signal generator with high output power, low phase noise, and I/Q modulation capability.

Specifications apply over a 0 to 55 °C range, unless otherwise stated, and apply after a 45 minute warm-up time. Supplemental characteristics, denoted as typical, nominal, or measured, provide additional (non-warranted) information at 25 °C, which may be useful in the application of the product.

Definitions

Specifications (spec): Represents warranted performance for instruments with a current calibration.

Typical (typ): Represents characteristic performance which is non-warranted. Describes performance that will be met by a minimum of 80% of all products.

Nominal (nom): Represents characteristic performance which is non-warranted. Represents the value of a parameter that is most likely to occur; the expected mean or mode of all instruments at room temperature (approximately 25 °C).

Measured: Represents characteristic performance which is non-warranted. Represents the value of a parameter measured on an instrument during design stage.



Table of Contents

Specifications	3
Frequency	3
Step (digital) sweep	3
Ramp (analog) sweep	4
Output	5
Spectral purity	7
Frequency modulation	12
Phase modulation	13
Amplitude modulation	13
External modulation inputs (Ext1 & Ext2)	14
Internal modulation source	14
Wideband AM	14
Pulse modulation	15
Narrow pulse modulation	15
Internal pulse generator	16
Simultaneous modulation	16
Vector modulation	17
Wideband external I/Q inputs	18
Internal baseband generator: arbitrary waveform mode	19
Internal baseband generator: real-time mode	22
Remote programming	24
General specifications	25
Input/Output Descriptions	26
Front panel connectors	26
Rear panel connectors	27
Auxiliary I/O connector	28
Options, Accessories, and Related Products	29
Web Resources	30
Related Agilent Literature	31

Specifications

Frequency

Range¹		
Option 520	250 kHz to 20 GHz	
Option 532	250 kHz to 31.8 GHz	
Option 544	250 kHz to 44 GHz	
Resolution		
CW	0.001 Hz	
All sweep modes	0.01 Hz ²	
Switching speed^{3, 4}		
< 16 ms (typ) with I/Q modulation off		
< 24 ms (typ) with I/Q modulation on		
Phase offset		
Adjustable in nominal 0.1 ° increments		
Frequency bands		
Band	Frequency range	N⁵
1	250 kHz to 250 MHz	1/8
2	> 250 to 500 MHz	1/16
3	> 500 MHz to 1 GHz	1/8
4	> 1 to 2 GHz	1/4
5	> 2 to 3.2 GHz	1/2
6	> 3.2 to 10 GHz	1
7	> 10 to 20 GHz	2
8	> 20 to 28.5 GHz	3
9	> 28.5 to 44 GHz	5
Accuracy		
± [(time since last adjustment x aging rate) + temperature effects + line voltage effects + calibration accuracy]		
Internal timebase reference oscillator		
Aging rate	Standard⁸ < ±3 x 10 ⁻⁸ /year or < ±2.5 x 10 ⁻¹⁰ /day after 30 days	Option UNX < ±3 x 10 ⁻⁸ /year or < ±2.5 x 10 ⁻¹⁰ /day after 30 days
Temperature effects (typ)	< ±4.5 x 10 ⁻⁹ 0 to 55 °C	< ±4.5 x 10 ⁻⁹ 0 to 55 °C
Line voltage effects (typ)	< ±2 x 10 ⁻¹⁰ for ±10% change	< ±2 x 10 ⁻¹⁰ for ±10% change
External reference frequency	10 MHz only	10 MHz only
Lock range	±1.0 ppm	±1.0 ppm
Reference output		
Frequency	10 MHz	
Amplitude	> +4 dBm into 50 Ω load (typ)	
External reference input		
Amplitude	5 dBm ±5 dB	
Option UNX	5 dBm ±5 dB ⁶	
Input impedance	50 Ω (nom)	
Operating modes		
Step sweep of frequency or amplitude or both (start to stop)		
List sweep of frequency or amplitude or both (arbitrary list)		
Sweep range		
Frequency sweep	Within instrument frequency range	
Amplitude sweep	Within attenuator hold range (see "Output" section)	
Dwell time	1 ms to 60 s	
Number of points	2 to 65535 (step sweep) 2 to 1601 per table (list sweep)	
Triggering	Auto, external, single, or GPIB	
Settling time		
Frequency	< 8 ms ⁷ (typ)	
Amplitude	< 5 ms (typ)	

Step (digital) sweep

- Operational, but unspecified, down to 100 kHz.
- In ramp sweep mode (Option 007), resolution is limited with narrow spans and slow sweep speeds. Refer to ramp sweep specifications for more information.
- Time from GPIB trigger to frequency within 0.1 ppm of final frequency above 250 MHz or within 100 Hz below 250 MHz.
- Add 12 ms (typ) when switching from greater than 3.2 GHz to less than 3.2 GHz.
- N is a factor used to help define certain specifications within the document.
- To optimize phase noise 5 dBm ± 2 dB.
- 19 ms (typ) when stepping from greater than 3.2 GHz to less than 3.2 GHz.
- Standard performance applies to units with serial numbers ending with 48050000 or greater. For units with lower serial numbers, refer to the data sheet shipped with the unit or the version of this document dated November 6, 2007.



Ramp (analog) sweep (Option 007)¹

Operating modes	<ul style="list-style-type: none"> Synthesized frequency sweep (start/stop), (center/span), (swept CW) Power (amplitude) sweep (start/stop) Manual sweep RPG control between start and stop frequencies Alternate sweep Alternates successive sweeps between current and stored states 		
Sweep span range	Settable from minimum ² to full range		
Maximum sweep rate	Start frequency	Maximum sweep rate	Max span for 100 ms sweep
	250 kHz to < 0.5 GHz	25 MHz/ms	2.5 GHz
	0.5 to < 1 GHz	50 MHz/ms	5 GHz
	1 to < 2 GHz	100 MHz/ms	10 GHz
	2 to < 3.2 GHz	200 MHz/ms	20 GHz
	≥ 3.2 GHz	400 MHz/ms	40 GHz
Frequency accuracy	± 0.05% of span ± timebase (at 100 ms sweep time, for sweep spans less than maximum values given above) Accuracy improves proportionally as sweep time increases ³		
Sweep time	(forward sweep, not including bandswitch and retrace intervals)		
Manual mode	Settable 10 ms to 200 seconds		
Resolution	1 ms		
Auto mode	Set to minimum value determined by maximum sweep rate and 8757D setting		
Triggering	Auto, external, single, or GPIB		
Markers	10 independent continuously variable frequency markers		
Display	Z-axis intensity or RF amplitude pulse		
Functions	M1 to center, M1/M2 to start/stop, marker delta		
Two-tone (master/slave) measurements⁴	Two PSGs can synchronously track each other, with independent control of start/stop frequencies		
Network analyzer compatibility	Fully compatible with Agilent 8757D scalar network analyzer ⁵ Also useable with Agilent 8757A/C/E and Gigatronics 8003 scalar network analyzers for making basic swept measurements. ⁶		

- During ramp sweep operation, AM, FM, phase modulation, and pulse modulation are useable but performance is not specified; wideband AM and I/Q modulation are not useable.
- Minimum settable sweep span is proportional to carrier frequency and sweep time. Actual sweep span may be slightly different than desired setting for spans less than $[0.00004\% \text{ of carrier frequency or } 140 \text{ Hz}] \times [\text{sweep time in seconds}]$. Actual span will always be displayed correctly.
- Typical accuracy for sweep times > 100 ms can be calculated from the equation: $[(0.005\% \text{ of span})/(\text{sweep time in seconds})] \pm \text{timebase}$. Accuracy is not specified for sweep times < 100 ms.
- For master/slave operation, use Agilent part number 8120-8806 master/slave interface cable.
- When measuring low-pass devices in AC mode, dynamic range may be reduced up to 10 dB below 3.2 GHz. An external highpass filter may be required to remove 27 kHz pulse source feed-through (11742A 45 MHz to 26.5 GHz blocking capacitor recommended).
- GPIB system interface is not supported with 8757A/C/E, only with 8757D. As a result, some features of the 8757A/C/E, such as frequency display, pass-through mode, and alternate sweep, do not function with PSG signal generators.

Output

Power ^{1,2} (dBm)	
Frequency range	spec (typ)
Option 520	
250 kHz to 3.2 GHz	-130 to +13 (+16)
250 kHz to 3.2 GHz with Option UNW	-130 to +9 (+13)
250 kHz to 3.2 GHz with Option 1EH	-130 to +10 (+13) ³
250 kHz to 3.2 GHz with Options UNW and 1EH	-130 to +7 (+12) ³
> 3.2 to 10 GHz	-130 to +18 (+23) ⁴
> 10 to 20 GHz	-130 to +18 (+22) ⁴
Options 532 and 544	
250 kHz to 3.2 GHz	-130 to +12 (+15)
250 kHz to 3.2 GHz with Option UNW	-130 to +8 (+12)
250 kHz to 3.2 GHz with Option 1EH	-130 to +9 (+12) ³
250 kHz to 3.2 GHz with Options UNW and 1EH	-130 to +6 (+11) ³
> 3.2 to 10 GHz	-130 to +14 (+21) ⁴
> 10 to 20 GHz	-130 to +14 (+18) ⁴
> 20 to 32 GHz	-130 to +14 (+18) ⁵
> 32 to 40 GHz	-130 to +12 (+18) ⁵
> 40 to 44 GHz	-130 to +10 (+13) ⁵
Step attenuator⁶	0 to 115 dB in 5 dB steps
Maximum available power in CW mode (measured)	



Attenuator hold range Minimum

From -15 dBm to maximum specified output power with step attenuator in 0 dB position. Can be offset using step attenuator.

Amplitude switching speed⁷



ALC on or off (without power search) < 3 ms (typ)

1. Maximum power specification is warranted from 15 to 35 °C, and is typical from 0 to 15 °C. Maximum power over the 35 to 55 °C range typically degrades less than 2 dB unless otherwise stated.
2. With I/Q modulation on, maximum power specification is typical. With external inputs enabled, $\sqrt{I^2 + Q^2} > 0.2 V_{rms}$.
3. With harmonic filters switched off. With filters on, maximum output power is reduced 3 dB for frequencies below 2 GHz.
4. With I/Q modulation on, maximum power specification is typically reduced 3 dB.
5. Maximum power over the 35 to 55 °C range typically degrades less than 4 dB. With I/Q modulation on, maximum power specification is typically reduced 5 dB.
6. The step attenuator provides coarse power attenuation to achieve low power levels. Fine power level adjustment is provided by the ALC (Automatic Level Control) within the attenuator hold range.
7. To within 0.1 dB of final amplitude within one attenuator range. Add 10 to 50 ms when using power search.

Level accuracy¹ (dB)				
Frequency	> +10 dBm	+10 to -10 dBm	< -10 to -70 dBm	< -70 to -90 dBm
250 kHz to 2 GHz	±0.6	±0.6	±0.7	±0.8
> 2 to 20 GHz	±0.8	±0.8	±0.9	±1.0
>20 to 32 GHz	±1.0	±0.9	±1.0	±1.7
> 32 to 44 GHz	±1.0	±0.9	±1.5	±2.0

CW level accuracy with I/Q modulation (With PRBS modulated data) (relative to CW)²	
<i>With ALC on:</i>	
QAM or QPSK formats ³	± 0.2 dB
Constant-amplitude formats (FSK, GMSK, etc)	± 0.2 dB
<i>With ALC off:⁴</i>	
	± 0.2 dB (typ)

Level accuracy (measured)



Resolution	0.01 dB
Temperature stability	0.01 dB/ °C (typ) ⁵
User flatness correction	
Number of points	2 to 1601 points/table
Number of tables	Up to 10,000, memory limited
Path loss	Arbitrary, within attenuator range
Entry modes	Remote power meter ⁶ , remote bus, manual (user edit/view)
Output impedance	50 Ω (nom)
SWR (internally leveled)	
250 kHz to 2 GHz	< 1.4:1 (typ)
> 2 GHz to 20 GHz	< 1.6:1 (typ)
> 20 GHz	< 1.8:1 (typ)
Leveling modes	Internal leveling, external detector leveling, millimeter source module, ALC off

- Specifications apply in CW and list/step sweep modes over the 15 to 35 °C temperature range, with attenuator hold off (normal operating mode). Degradation outside this range, for ALC power levels > -5 dBm, is typically < 0.3 dB. In ramp sweep mode (with Option 007), specifications are typical. For instruments with Type-N connectors (Option 1ED), specifications apply to 18 GHz only. From 18 to 20 GHz, typical level accuracy degrades by 0.2 dB. Specifications do not apply above the maximum specified power.
- If external inputs are used, specification applies with input level $\sqrt{I^2 + Q^2} = 0.3 V_{rms}$ and I/Q modulator attenuation is internally optimized based on input levels.
- Measured with symbol rate > 10 kHz and power ≤ 0 dBm.
- Relative to ALC on, after power search is executed. When applying external I/Q signals with ALC off, output level will vary directly with I/Q input level.
- Options 532 and 544: 0.02 dB/°C (typ) above 2 GHz.
- Compatible with Agilent EPM Series (E4418B and E4419B) power meters.

External detector leveling

Range	-0.2 mV to -0.5 V (nom) (-36 dBm to +4 dBm using Agilent 33330D/E detector)
Bandwidth	Selectable 0.1 to 100 kHz (nom) (Note: not intended for pulsed operation)

Maximum reverse power 1/2 Watt, 0 V_{DC}

Spectral purity




Harmonics¹ (at +10 dBm or maximum specified output power, whichever is lower)

< 10 MHz -28 dBc (typical below 1 MHz)

10 MHz to 2 GHz -30 dBc^{2,3}10 MHz to 2 GHz (with Option 1EH filters on) -55 dBc⁴

> 2 GHz to 20 GHz -55 dBc

> 20 GHz to 44 GHz -45 dBc

Harmonics (measured)

-
1. Specifications are typical for harmonics beyond specified frequency range.
 2. Specification applies to units with serial numbers ending with 45160000 or greater. For serial numbers below that, the specification is -28 dBc.
 3. Typical below 250 MHz if Option 1EH is installed and the filters are off.
 4. In ramp sweep mode (Option 007), harmonics are -30 dBc below 250 MHz.

Sub-harmonics¹	(At +10 dBm or maximum specified output power, whichever is lower)	
250 kHz to 10 GHz	None	
> 10 GHz to 20 GHz	< -60 dBc	
> 20 GHz to 44 GHz	< -45 dBc	
Non-harmonics²	(dBc at +10 dBm or maximum specified output power, whichever is lower, for offsets > 3 kHz [> 300 Hz with Option UNX])	
Frequency	Spec	Typical
250 kHz to 250 MHz	-65	-72 for > 10 kHz offsets
> 250 MHz to 1 GHz	-80	-88
> 1 to 2 GHz	-74	-82
> 2 to 3.2 GHz	-68	-76
> 3.2 to 10 GHz	-62	-70
> 10 to 20 GHz	-56	-64
> 20 to 28.5 GHz	-52	-60
> 28.5 to 44 GHz	-48	-56
SSB phase noise (CW)³	20 kHz offset from carrier (dBc/Hz)	
Frequency	Spec	Typical
250 kHz to 250 MHz	-130	-134
> 250 to 500 MHz	-134	-138
> 500 MHz to 1 GHz	-130	-134
> 1 to 2 GHz	-124	-128
> 2 to 3.2 GHz	-120	-124
> 3.2 to 10 GHz	-110	-113
> 10 to 20 GHz	-104	-108
> 20 to 28.5 GHz	-100	-104
> 28.5 GHz	-96	-100

1. Sub-harmonics are defined as Carrier Freq / N). Specifications are typical for sub-harmonics beyond specified frequency range.
2. Performance is typical for spurs at frequencies above the maximum operating frequency of the instrument. Specifications apply for CW mode, without modulation. In ramp sweep mode (Option 007), performance is typical for offsets > 1 MHz.
3. Measured at +10 dBm or maximum specified output power, whichever is less.

Option UNX: Absolute SSB phase noise (CW)^{1, 2}

Frequency	Offset from carrier and Phase Noise (dBc/Hz)					
	1 Hz	10 Hz	100 Hz	1 kHz	10 kHz	100 kHz
	Spec (typ)	Spec (typ)	Spec (typ)	Spec (typ)	Spec (typ)	Spec (typ)
250 kHz to 250 MHz	-58 (-66)	-87 (-94)	-104 (-120)	-121 (-128)	-128 (-132)	-130 (-133)
> 250 to 500 MHz	-61 (-72)	-88 (-98)	-108 (-118)	-126 (-132)	-132 (-136)	-136 (-141)
> 500 MHz to 1 GHz	-57 (-65)	-84 (-93)	-101 (-111)	-121 (-130)	-130 (-134)	-130 (-135)
> 1 to 2 GHz	-51 (-58)	-79 (-86)	-96 (-106)	-115 (-124)	-124 (-129)	-124 (-129)
> 2 to 3.2 GHz	-46 (-54)	-74 (-82)	-92 (-102)	-111 (-120)	-120 (-124)	-120 (-124)
> 3.2 to 10 GHz	-37 (-44)	-65 (-72)	-81 (-92)	-101 (-109)	-110 (-114)	-110 (-115)
> 10 to 20 GHz	-31 (-38)	-59 (-66)	-75 (-87)	-95 (-106)	-104 (-107)	-104 (-109)
> 20 to 28.5 GHz	-25 (-34)	-56 (-62)	-72 (-83)	-92 (-102)	-100 (-103)	-100 (-105)
> 28.5 to 44 GHz	-20 (-30)	-51 (-58)	-68 (-77)	-88 (-97)	-96 (-99)	-96 (-101)

Option UNX: Residual SSB phase noise (CW)^{1, 2}

Frequency	Offset from carrier and Phase Noise (dBc/Hz)					
	1 Hz	10 Hz	100 Hz	1 kHz	10 kHz	100 kHz
	Spec (typ)	Spec (typ)	Spec (typ)	Spec (typ)	Spec (typ)	Spec (typ)
250 kHz to 250 MHz	(-94)	-100 (-107)	-110 (-118)	-120 (-126)	-128 (-132)	-130 (-133)
> 250 to 500 MHz	(-101)	-105 (-112)	-115 (-122)	-124 (-131)	-132 (-136)	-136 (-141)
> 500 MHz to 1 GHz	(-94)	-100 (-107)	-110 (-118)	-120 (-126)	-130 (-134)	-130 (-134)
> 1 to 2 GHz	(-89)	-96 (-101)	-104 (-112)	-114 (-120)	-124 (-129)	-124 (-129)
> 2 to 3.2 GHz	(-85)	-92 (-97)	-100 (-108)	-110 (-116)	-120 (-124)	-120 (-124)
> 3.2 to 10 GHz	(-74)	(-87)	(-98)	(-106)	(-114)	(-115)


Residual FM	(RMS, 50 Hz to 15 kHz bandwidth)
CW mode	< N x 8 Hz (typ)
CW mode with Option UNX	< N x 4 Hz (typ)
Ramp sweep mode	< N x 1 kHz (typ)
Broadband noise	(CW mode at +10 dBm or maximum specified output power, whichever is lower, for offsets > 10 MHz)
> 2.4 to 20 GHz	< -148 dBc/Hz (typ)
> 20 GHz	< -141 dBc/Hz (typ)

1. Phase noise specifications are warranted from 15 to 35 °C.


2. Measured at +10 dBm or maximum specified power, whichever is less.

Measured phase noise with an Agilent E5500 phase noise measurement system and plotted without spurs


Standard phase noise²




Standard phase noise with I/Q modulation on^{1,2}



Option UNX phase noise




Option UNX phase noise with I/Q modulation on¹




1. External I/Q input level $\sqrt{I^2 + Q^2} = 250$ mVrms, I/Q modulator attenuator set to auto.

2. Measured standard performance applies to units with serial numbers ending with 48050000 or greater. For units with lower serial numbers, refer to the data sheet shipped with the unit or the version of this document dated November 6, 2007.

Option UNX phase noise



AM noise at 10 GHz



Measured RMS jitter:¹*Standard*

Carrier frequency	SONET/SDH data rates	RMS jitter bandwidth	Unit intervals (μ UI)	Time (fs)
155 MHz	155 MB/s	100 Hz to 1.5 MHz	25	158
622 MHz	622 MB/s	1 kHz to 5 MHz	21	34
2.488 GHz	2488 MB/s	5 kHz to 20 MHz	57	23
9.953 GHz	9953 MB/s	10 kHz to 80 MHz	152	15
39.812 GHz	39812 MB/s	40 kHz to 320 MHz	627	16

Option UNX

Carrier frequency	SONET/SDH data rates	RMS jitter bandwidth	Unit intervals (μ UI)	Time (fs)
155 MHz	155 MB/s	100 Hz to 1.5 MHz	23	151
622 MHz	622 MB/s	1 kHz to 5 MHz	19	30
2.488 GHz	2488 MB/s	5 kHz to 20 MHz	56	22
9.953 GHz	9953 MB/s	10 kHz to 80 MHz	152	15
39.812 GHz	39812 MB/s	40 kHz to 320 MHz	626	16

Frequency modulation

(Option UNT)

Maximum deviation ²	Frequency	Maximum deviation
	250 kHz to 250 MHz	2 MHz
	> 250 to 500 MHz	1 MHz
	> 500 MHz to 1 GHz	2 MHz
	> 1 GHz to 2 GHz	4 MHz
	> 2 GHz to 3.2 GHz	8 MHz
	> 3.2 GHz to 10 GHz	16 MHz
	> 10 GHz to 20 GHz	32 MHz
	> 20 GHz to 28.5 GHz	48 MHz
	> 28.5 GHz to 44 GHz	80 MHz
Resolution	0.1% of deviation or 1 Hz, whichever is greater	
Deviation accuracy	< $\pm 3.5\%$ of FM deviation + 20 Hz (1 kHz rate, deviations < N x 800 kHz)	
Modulation frequency response³ (at 100 kHz deviation)		
Path [coupling]	1 dB bandwidth	3 dB bandwidth (typ)
FM path 1 [DC]	DC to 100 kHz	DC to 10 MHz
FM path 2 [DC]	DC to 100 kHz	DC to 1 MHz
FM path 1 [AC]	20 Hz to 100 kHz	5 Hz to 10 MHz
FM path 2 [AC]	20 Hz to 100 kHz	5 Hz to 1 MHz
DC FM⁴ carrier offset	$\pm 0.1\%$ of set deviation + (N x 8 Hz)	
Distortion	< 1% (1 kHz rate, deviations < N x 800 kHz)	
Sensitivity	$\pm 1 V_{\text{peak}}$ for indicated deviation	
Paths	FM1 and FM2 are summed internally for composite modulation. Either path may be switched to any one of the modulation sources: Ext1, Ext2, internal1, internal2. The FM2 path is limited to a maximum rate of 1 MHz. The FM2 path must be set to a deviation less than FM1.	

1. Calculated from phase noise performance in CW mode only at +10 dBm. For other frequencies, data rate, or bandwidths, please contact your sales representative.

2. Through any combination of path1, path2, or path1 + path2.

3. Specifications apply in CW and list/step sweep modes. During ramp sweep operation (Option 007), 3 dB bandwidth is typically 50 kHz to 10 MHz (FM1 path), and 50 kHz to 1 MHz (FM2 path).

4. At the calibrated deviation and carrier frequency, within 5 °C of ambient temperature at time of user calibration.

Phase modulation (Option UNT)

Maximum deviation ¹	Frequency	Normal BW mode	High BW mode
	250 kHz to 250 MHz	20 rad	2 rad
	> 250 to 500 MHz	10 rad	1 rad
	> 500 MHz to 1 GHz	20 rad	2 rad
	> 1 GHz to 2 GHz	40 rad	4 rad
	> 2 GHz to 3.2 GHz	80 rad	8 rad
	> 3.2 GHz to 10 GHz	160 rad	16 rad
	> 10 GHz to 20 GHz	320 rad	32 rad
	> 20 GHz to 28.5 GHz	480 rad	48 rad
	> 28.5 GHz to 44 GHz	800 rad	80 rad
Resolution	0.1% of set deviation		
Deviation accuracy	< ±5% of deviation + 0.01 radians (1 kHz rate, normal BW mode)		
Modulation frequency response²			
	Normal BW mode	High BW mode	
Rates (3 dB BW)	DC to 100 kHz	DC to 1MHz (typ) ³	
Distortion	< 1 % (1 kHz rate, Total Harmonic Distortion (THD), dev < N x 80 rad, normal BW mode)		
Sensitivity	±1 V _{peak} for indicated deviation		
Paths	ΦM1 and ΦM2 are summed internally for composite modulation. Either path may be switched to any one of the modulation sources: Ext1, Ext2, internal1, internal2. The ΦM2 path must be set to a deviation less than ΦM1.		

Amplitude modulation⁴ (Option UNT) (typical)

Depth	Linear mode	Exponential (log) mode (downward modulation only)
Maximum		
ALC On	> 90%	> 20 dB
ALC Off with power search ⁵ or ALC On with Deep AM ⁶	> 95%	> 40 dB
Settable	0 to 100 %	0 to 40 dB
Resolution	0.1%	0.01 dB
Accuracy (1 kHz rate)	< ±(6 % of setting + 1 %)	< ±(2% of setting + 0.2 dB)
Ext sensitivity	±1 V _{peak} for indicated depth	-1 V _{peak} for indicated depth
Rates (3 dB bandwidth, 30% depth)		
DC coupled	0 to 100 kHz	
AC coupled	10 Hz to 100 kHz (useable to 1 MHz)	
Distortion (1 kHz rate, linear mode, Total Harmonic Distortion (THD))		
30% AM	< 1.5%	
60% AM	< 2 %	
Paths	AM1 and AM2 are summed internally for composite modulation. Either path may be switched to any one of the modulation sources: Ext1, Ext2, internal1, internal2.	

1. Through any combination of path1, path2, or path1 + path2.

2. Specifications apply in CW and list/step sweep modes. During ramp sweep operation (Option 007), 3 dB bandwidth is typically 50 kHz to 1 MHz (high BW mode).

3. Path 1 is useable to 4 MHz for external inputs less than 0.3 V_{peak}.

4. AM specifications are typical. For carrier frequencies below 2 MHz, AM is useable but not specified. Unless otherwise stated, specifications apply with ALC on and envelope peaks within ALC operating range (-15 dBm to maximum specified power, excluding step attenuator setting).

5. ALC Off is used for narrow pulse modulation and/or high AM depths, with envelope peaks below ALC operating range. Carrier power level will be accurate after a Power Search is executed.

6. ALC On with Deep AM provides high AM depths together with closed-loop internal leveling. This mode can be used with a repetitive AM waveform (frequency > 10 Hz) with peaks > -5 dBm (nominal, excluding step-attenuator setting).

External modulation inputs (Ext1 & Ext2) (Option UNT)

Modulation types	AM, FM, and Φ M
Input impedance	50 or 600 Ω (nom), switched
High/low indicator (100 Hz to 10 MHz BW, ac coupled inputs only)	Activated when input level error exceeds 3% (nom)

Internal modulation source (Option UNT)

Dual function generators provide two independent signals (internal1 and internal2) for use with AM, FM, Φ M, or LF Out.	
Waveforms	Sine, square, positive ramp, negative ramp, triangle, Gaussian noise, uniform noise, swept sine, dual sine ¹
Rate range	
Sine	0.5 Hz to 1 MHz
Square, ramp, triangle	0.5 Hz to 100 kHz
Resolution	0.5 Hz
Accuracy	Same as timebase
LF out	
Output	Internal1 or internal2. Also provides monitoring of internal1 or internal2 when used for AM, FM, or Φ M.
Amplitude	0 to 3 V _{peak} , into 50 Ω (nom)
Output impedance	50 Ω (nom)
Swept sine mode: (frequency, phase continuous)	
Operating modes	Triggered or continuous sweeps
Frequency range	1 Hz to 1 MHz
Sweep rate	0.5 to 100,000 sweeps/s, equivalent to sweep times 10 μ s to 2 s
Resolution	0.5 Hz (0.5 sweep/s)

Wideband AM

Rate (typical 1 dB bandwidth)	
ALC on	1 kHz to 80 MHz
ALC off	DC to 80 MHz
External I input	
Sensitivity	0.5 V = 100%
Input impedance	50 Ω (nom)

1. Internal2 is not available when using swept sine or dual sine modes.

Pulse modulation^{1,2}
(Option UNU)


	500 MHz to 3.2 GHz	Above 3.2 GHz
On/Off ratio	80 dB (typ)	80 dB
Rise/Fall times (Tr, Tf)	100 ns (typ)	6 ns (typ)
Minimum pulse width		
Internally leveled	2 μ s	1 μ s
Level hold (ALC off with power search)	0.5 μ s	0.15 μ s
Repetition frequency		
Internally leveled	10 Hz to 250 kHz	10 Hz to 500 kHz
Level hold (ALC off with power search)	DC to 1 MHz	DC to 3 MHz
Level accuracy (relative to CW)		
Internally leveled	± 0.5 dB	± 0.5 dB
Level hold (ALC off with power search)	± 0.5 dB (typ)	± 0.5 dB (typ)
Width compression		
(RF width relative to video out)	± 50 ns (typ)	± 5 ns (typ)
Video feed-through³	< 200 mv (typ)	< 2 mv (typ)
Video delay (Ext input to video)	50 ns (nom)	50 ns (nom)
RF delay (video to RF output)	270 ns (nom)	35 ns (nom)
Pulse overshoot	< 10% (typ)	< 10% (typ)
Input level	+1 V _{peak} = RF On	+1 V _{peak} = RF On
Input impedance	50 Ω (nom)	50 Ω (nom)

Narrow pulse modulation^{1,2}
(Option UNW)

	10 MHz to 3.2 GHz	Above 3.2 GHz
On/Off ratio	80 dB	80 dB
Rise/Fall times (Tr, Tf)	10 ns (8 ns typ)	10 ns (6 ns typ)
Minimum pulse width		
Internally leveled:	1 μ s	1 μ s
Level hold (ALC off with power search):	20 ns	20 ns
Repetition frequency		
Internally leveled:	10 Hz to 500 kHz	10 Hz to 500 kHz
Level hold (ALC off with power search):	DC to 5 MHz	DC to 10 MHz
Level accuracy (relative to CW)		
Internally leveled	± 0.5 dB	± 0.5 dB (0.15 dB typ)
Level hold (ALC off with power search):	± 1.3 dB (typ)	± 0.5 dB (typ)


1. With ALC off, specifications apply after the execution of power search. Specifications apply with Atten Hold Off (default mode), or ALC level between -5 and $+10$ dBm or maximum specified power, whichever is lower.
2. Power search is a calibration routine that improves level accuracy with ALC off. The instrument microprocessor momentarily closes the ALC loop to find the modulator drive setting necessary to make the quiescent RF level equal to an entered value, then opens the ALC loop while maintaining that modulator drive setting. When executing power search, RF power will be present for typically 10-50 ms; the step attenuator can be set to automatically switch to maximum attenuation to protect sensitive devices. Power search can be configured to operate either automatically or manually at the carrier frequency, or over a user-definable frequency range.
3. With attenuator in 0 dB position. Video feed-through decreases with attenuator setting.

	10 MHz to 3.2 GHz	Above 3.2 GHz
Width compression (RF width relative to video out)	±5 ns (typ)	±5 ns (typ)
Video feed-through¹	< 125 mV pk-pk (typ)	< 2 mV pk-pk (typ)
Video delay (Ext input to video)	50 ns (nom)	50 ns (nom)
RF delay (video to RF output)	45 ns (nom)	35 ns (nom)
Pulse overshoot	< 15% (typ)	< 10% (typ)
Input level	+1 V _{peak} = RF On	+1 V _{peak} = RF On
Input impedance	50 Ω (nom)	50 Ω (nom)



Internal pulse generator (Option UNU or UNW)

Modes	Free-run, triggered, triggered with delay, doublet, and gated. Triggered with delay, doublet, and gated modes require an external trigger source.
Period (PRI) (Tp)	70 ns to 42 s (Repetition frequency: 0.024 Hz to 14.28 MHz)
Pulse width (Tw)	10 ns to 42 s
Delay (Td)	
Free-run mode	0 to ±42 s
Triggered with delay and doublet modes	75 ns to 42 s with ±10 ns jitter
Resolution	10 ns (width, delay, and PRI)



Simultaneous modulation

All modulation types (FM, AM, Φ M, pulse, and I/Q) may be simultaneously enabled except: FM with Φ M, linear AM with exponential AM, and wideband AM with I/Q. AM, FM, and Φ M can sum simultaneous inputs from any two sources (Ext1, Ext2, internal1, or internal2). Any given source (Ext1, Ext2, internal1, or internal2) may be routed to only one activated modulation type.

1. With attenuator in 0 dB position. Video feed-through decreases with attenuator setting.

Vector modulation¹

External I/Q inputs

Input impedance switched

50 or 600 Ω (nom)

Input range²


Minimum 0.1 V_{rms} , maximum $1V_{\text{peak}}$

Flatness


± 1 dB within ± 40 MHz of carrier (with ALC off) (typ)

I/Q frequency response³ (measured)


900 MHz




1.8 GHz



2.4 GHz



38 GHz



RF path filters

Carrier frequency

≤ 250 MHz
 > 250 to 396 MHz
 > 396 to 628 MHz
 > 628 to 1000 MHz
 > 1.0 to 1.5 GHz

Nominal filter cutoff

300 MHz low-pass filter
 220 to 420 MHz bandpass filter
 350 to 650 MHz bandpass filter
 1040 MHz low-pass filter
 1.6 GHz low-pass filter

1. With Option 007, vector modulation is not useable in ramp sweep mode. With Option 1EH, specifications apply with filters off.
2. For optimum signal quality, the I and Q inputs should be $0.7 V_{\text{peak}}$, with $\sqrt{I^2 + Q^2} + 150$ mV_{rms}. Different RMS levels are accommodated by adjusting the internal I/Q modulator attenuator, which may be either manually or automatically set. The minimum input level required to maintain RF level accuracy is $\sqrt{I^2 + Q^2} = 0.1 V_{\text{rms}}$.
3. Sine wave response, measured with input level = 100 mV_{rms} on one channel, and ALC off. For carrier frequencies below 1.5 GHz, modulation frequency response within ± 150 MHz of carrier may be limited by RF chain filtering.


I/Q adjustments	
I & Q offsets	External inputs (600 Ω): ± 5 Volts External inputs (50 Ω): ± 50 % Internal baseband generator: ± 50 %
I/Q attenuation	0 to 40 dB
I/Q gain balance	± 4 dB
I/Q quadrature skew	$\pm 10^\circ$ range (typ)
Low pass filter	Selectable 40 MHz or through path
I/Q baseband outputs	
Differential	I, \bar{I} , Q, \bar{Q}
Single ended	I, Q
Frequency range	DC to 40 MHz
Output voltage into 50 Ω	1.5 V _{peak-to-peak} (typ)
DC offset adjustments	± 3 V
DC offset resolution	1 mV
Low pass filter	Selectable 40 MHz or through path

Wideband external differential I/Q inputs¹ (Option 016)


RF output frequency range	250 kHz to 3.2 GHz	3.2 to 44 GHz
Input		
Input (baseband) frequency range	DC to 130 MHz (nom)	DC to 1.0 GHz ²
Input impedance	50 Ω (nom)	50 Ω (nom)
Recommended input level	-1 dBm	0 dBm (nom)
Maximum input voltage	± 1 V _{DC}	± 1 V _{DC}
I/Q offset adjustments	± 50 %	± 50 %
I/Q quadrature skew	± 10 degrees	± 10 degrees (nom)
I/Q frequency response (measured)		

I/Q frequency response³ for frequencies < 3.2 GHz (measured)


900 MHz




1087.5 MHz



1.8 GHz




2.4 GHz




1. With Option 007, vector IQ modulation is not useable in ramp sweep mode.
2. Modulation frequency response within ± 1 GHz of the carrier frequency may be limited by the RF chain cutoff frequencies.
3. Sine wave response, measured with input level = 100 mVrms on one channel, and ALC off. For carrier frequencies below 1.5 GHz, modulation frequency response within ± 150 MHz of carrier may be limited by RF chain filtering.

**I/Q frequency response¹
for frequencies > 3.2 GHz
(measured)**


10 GHz




12 GHz



15 GHz



20 GHz



RF path filters²

Carrier frequency	Nominal filter cutoff frequencies
> 3.2 to 5 GHz	5.5 GHz low-pass filter
> 5 to 8 GHz	8.9 GHz low-pass filter
> 8 to 12.8 GHz	13.9 GHz low-pass filter
> 12.8 to 20 GHz	22.5 GHz low-pass filter
> 20 to 24 GHz	19.6 to 24.5 GHz band-pass filter
> 24 to 28.5 GHz	23.5 to 29.0 GHz band-pass filter
> 28.5 to 32 GHz	28.0 to 32.5 GHz band-pass filter
> 32 to 36 GHz	31.7 to 36.5 GHz band-pass filter
> 36 to 40 GHz	35.5 to 40.4 GHz band-pass filter
> 40 to 44 GHz	39.5 to 44.3 GHz band-pass filter

**Internal baseband generator:
arbitrary waveform mode
(Options 602)**


Channels	2 [I and Q]
Resolution	16 bits [1/65,536]
Baseband waveform memory	
Length (playback)	
Option 602	64 megasamples (MSa/channel)
Length (non-volatile storage)	1.2 gigasamples (GSa) on 8 GB removable flash memory (Option 009)
Waveform segments	
Segment length	60 samples to 8 or 64 MSa
Maximum number of segments	8,192 (Option 602)
Minimum memory allocation	256 samples or 1 kbyte blocks
Waveform sequences	
Sequencing	Continuously repeating
Maximum number of sequences	16,384
Maximum segments/sequence	32,768
Maximum segment repetitions	65,536

1. Sine wave response, measured with input level = 100 mVrms on one channel, and ALC off. For carrier frequencies below 1.5 GHz, modulation frequency response within ± 150 MHz of carrier may be limited by RF chain filtering.

2. Modulation frequency response within ± 1 GHz of the carrier frequency may be limited by the RF chain cutoff frequencies. For operation near a filter edge, filters can be bypassed using software commands to increase modulation bandwidth.


Clock	
Sample rate	1 Hz to 100 MHz
Resolution	0.001 Hz
Accuracy	Same as timebase +2 ⁻⁴² [in non-integer applications]
Reconstruction filter: [fixed]	50 MHz [used for all symbol rates]
Baseband spectral purity	
[full scale sinewave]	
Harmonic distortion	100 kHz to 2 MHz: < -65 dBc (typ)
Phase noise	< -127 dBc/Hz (typ) (baseband output of 10 MHz sinewave at 20 kHz offset)
IM performance	< -74 dB (typ)
Triggers	
Types	Continuous, single, gated, segment advance
Source	Trigger key, external, remote [LAN, GPIB, RS-232]
External polarity	Negative, positive
External delay time	10 ns to 40 s plus latency
External delay resolution	10 ns
Markers	
<i>(Markers are defined in a segment during the waveform generation process, or from the PSG front panel. A marker can also be tied to the RF blanking feature of the PSG.)</i>	
Marker polarity	Negative, positive
Number of markers	4
Multicarrier	
Number of carriers	Up to 100 (limited by a maximum bandwidth of 80 MHz depending on symbol rate and modulation type)
Frequency offset (per carrier)	-40 MHz to +40 MHz
Power offset (per carrier)	0 dB to -40 dB
Modulation	
PSK	Types BPSK, QPSK, OQPSK, $\pi/4$ DQPSK, 8PSK, 16PSK, D8PSK
QAM	4, 16, 32, 64, 128, 256
FSK	Selectable: 2, 4, 8, 16
MSK	
Data	Random ONLY
Multicarrier (measured)	

4 Carriers with 64 QAM at 10 Msym/s with 20 MHz spacing




Multitone	
Number of tones	2 to 64, with selectable on/off state per tone
Frequency spacing	100 Hz to 80 MHz
Phase (per tone)	Fixed or random
Power offset (per tone)	0 to -40 dB


20 GHz multitone (measured)




20 GHz image rejection (measured)



44 GHz multitone (measured)



44 GHz image rejection (measured)




Two-tone

Frequency spacing
Alignment
IM distortion¹
250 kHz to 3.2 GHz
> 3.2 GHz to 20 GHz
> 20 to 40 GHz
> 40 to 44 GHz


100 Hz to 80 MHz
Left, centered, or right

< -45 dBc (typ)
< -55 dBc (typ)
< -50 dBc (typ)
< -45 dBc (typ)

20 GHz two tone (measured)





44 GHz two tone (measured)



1. RF power < 0 dBm (Option 520) or < -3 dBm (Option 532, 544). When external inputs are used, vector accuracy is equivalent to internal performance after system calibration.

**Internal baseband generator:
real-time mode
(Option 602)**

Basic modulation types (custom format)	
PSK	BPSK, QPSK, OQPSK, $\pi/4$ DQPSK, 8PSK, 16PSK, D8PSK
MSK	User-defined phase offset from 0 to 100 °
QAM	4, 16, 32, 64, 128, 256
FSK	Selectable: 2, 4, 8, 16 level symmetric, C4FM User defined: Up to 16 custom deviation levels Deviation resolution: 0.1 Hz
	Symbol rate Maximum deviation
	< 5 MHz 4 times symbol rate
	5 MHz to 50 MHz 20 MHz
User-defined I/Q	Custom map of 256 unique values
Vector accuracy ¹	Formats: BPSK, QPSK, 16-256 QAM ($\alpha = 0.3$, root Nyquist filter, symbol rate 4 Msym/s)
EVM (% RMS)	
≤ 20 GHz	< 1.2%, < 0.8% (typ)
> 20 to 32 GHz	< 1.3% < 0.9% (typ)
> 32 to 44 GHz	< 1.4% < 0.9% (typ)
Origin offset	
250 kHz to 3.2 GHz	-45 dBc (typ)
3.2 to 44 GHz	-50 dBc (typ)
EVM (measured)	




FIR filter	
Selectable	Nyquist, root Nyquist, Gaussian, rectangular α : 0 to 1, B_bT : 0.1 to 1
Custom FIR	16-bit resolution, up to 64 symbols long, automatically resampled to 1024 coefficients (maximum) > 32 to 64 symbol filter: symbol rate ≤ 12.5 MHz > 16 to 32 symbol filter: symbol rate ≤ 25 MHz Internal filters switch to 16 tap when symbol rate is between 25 and 50 MHz
Symbol rate	
For external serial data:	Adjustable from 1000 symbols/sec to a maximum symbol rate of 50 Mbits/sec ÷ (#bits/symbol)
For internally generated data:	Adjustable from 1000 symbols/sec to 50 Msymbols/second and a maximum of 8 bits per symbol. Modulation quality may be degraded at high symbol rates.


1. Measured with Agilent 89441A vector signal analyzer. Valid after executing I/Q calibration, and instrument is maintained within ±5 °C of calibration temperature. RF power < 0 dBm (Option 520) or < -3 dBm (Option 532, 544). When external inputs are used, vector accuracy is equivalent to internal performance, after system calibration.

Baseband reference frequency	Data clock can be phase locked to an external reference.
Input	ECL, CMOS, TTL compatible, 50 Ω AC coupled
Frame trigger delay control	
Range	0 to 1,048,575 bits
Resolution	1 bit
Data types	
Internally generated data	
Pseudo-random patterns	PN9, PN11, PN15, PN20, PN23
Repeating sequence	Any 4-bit sequence Other fixed patterns
Direct-pattern RAM [PRAM]	
Max size	64 Mb (Option 602) (each bit uses an entire sample space)
Use	Non-standard framing
User file	
Max size	6.4 Mb (Option 602)
Use	Continuous modulation or internally generated TDMA standard
Externally generated data	
Type	Serial data
Inputs	Data, data (bit) clock, symbol sync Accepts data rates $\pm 5\%$ of specified data rate
Internal burst shape control	
Varies with standards and bit rates	
Rise/Fall time range	Up to 30 bits
Rise/Fall delay range	0 to 63.5 bits
Spectral re-growth (measured)	

10 GHz carrier with 16 QAM signal at 10 Msym/s



25 GHz carrier with 16 QAM signal at 10 Msym/s



Remote programming

Interfaces	GPIB (IEEE-488.2,1987) with listen and talk, RS-232, and 10BaseT LAN interface
Control languages	SCPI version 1997.0. Completely code compatible with previous PSG signal generator models: <ul style="list-style-type: none">• E8241A• E8244A• E8251A• E8254A• E8247C• E8257C The E8267D will emulate the applicable commands for the following signal generators, providing general compatibility with ATE systems: Agilent: <ul style="list-style-type: none">• 8340-series (8340/41B)• 8360-series (836xxB/L)• 83700-series (837xxB)• 8662A/63A Non-Agilent: <ul style="list-style-type: none">• Anritsu MG3690-series
IEEE-488 functions	SH1, AH1, T6, TE0, L4, LE0, SR1, RL1, PP0, DC1, DT0, C0, E2
ISO compliant	This family of signal generators is manufactured in an ISO-9001 registered facility in concurrence with Agilent Technologies' commitment to quality.
Agilent IO Libraries	Agilent's IO Libraries Suite ships with the E8267D to help you quickly establish an error-free connection between your PC and instruments – regardless of the vendor. It provides robust instrument control and works with the software development environment you choose.

General specifications

Power requirements	100-120 V 50/60 Hz, 220-240 V 50/60 Hz (automatically selected) < 400 W typ 650 W maximum
Operating temperature range	0 to 55 °C ¹
Storage temperature range¹	-40 to 70 °C
Altitude	0 to 4600 m (15,00 ft)
Humidity	80% relative humidity (maximum) for temperatures up to 31 °C, decreasing linearly to 50% relative humidity at 40 °C.
Environmental Testing	Samples of this product have been type tested in accordance with the Agilent Environmental Test Manual and verified to be robust against the environmental stresses of storage, transportation and end-use; those stresses include but are not limited to temperature, humidity, shock, vibration, altitude and power line conditions. Test methods are aligned with IEC 60068-2 and levels are similar to MIL-PRF-28800F Class 3. ²
EMC	Meets the conducted and radiated interference and immunity requirements of IEC/EN 61326-1. Meets radiated emission requirements of CISPR Pub 11/1997 Group 1 class A.
Storage	Memory is shared by instrument states, user data files, sweep list files, and waveform sequences. There is 14 MB of flash memory available in the E8267D PSG. With Option 009, there is an additional 8 GB of storage. Depending on how the memory is utilized, a maximum of 1000 instrument states can be saved.
Security	Display blanking Memory clearing functions (See Application Note "Security Features of Agilent Technologies Signal Generators", Part Number E4400- 90621.) With Option 009, all user-written files are stored on an 8 GByte removable flash memory card.
Compatibility	Agilent 83550 Series Millimeter Heads and OML millimeter source modules Agilent 8757D scalar network analyzers Gigatronics 8003 scalar network analyzer Agilent EPM Series power meters
Self-test	Internal diagnostic routine tests most modules (including microcircuits) in a preset condition. For each module, if its node voltages are within acceptable limits, then the module "passes" the test.
Weight	< 25 kg (54 lb.) net, < 33 kg (74 lb.) shipping
Dimensions	178 mm H x 426 mm W x 515 mm D (7" H x 16.8" W x 20.3" D)
Recommended calibration cycle	24 months

1. Storage below -20 °C instrument states may be lost.

2. As is the case with all signal generation equipment, phase noise specifications are not warranted in a vibrating environment.

Input/Output Descriptions

Front panel connectors

(All connectors are BNC female unless otherwise noted.)¹

RF output	Output impedance 50 Ω (nom)
Option 520	Precision APC-3.5 male or precision Type-N female with Option 1ED
Options 532 and 544	Precision 2.4 mm male; plus 2.4(f) - 2.4(f) mm and 2.4(f) - 2.9(f) mm adaptors
ALC input	Used for negative external detector leveling Nominal input impedance 120 k Ω , damage level ± 15 V.
LF output	Outputs the internally generated LF source. Nominal output impedance 50 Ω .
External input 1	Drives either AM, FM, or Φ M. Nominal input impedance 50 or 600 Ω , damage levels are 5 V_{rms} and 10 V_{peak} .
External input 2	Drives either AM, FM, or Φ M. Nominal input impedance 50 or 600 Ω , damage levels are 5 V_{rms} and 10 V_{peak} .
Pulse/trigger gate input	Accepts input signal for external fast pulse modulation. Also accepts external trigger pulse input for internal pulse modulation. Nominal impedance 50 Ω . Damage levels are 5 V_{rms} and 10 V_{peak} .
Pulse video out	Outputs a signal that follows the RF output in all pulse modes. TTL-level compatible, nominal source impedance 50 Ω .
Pulse sync out	Outputs a synchronizing pulse, nominally 50 ns width, during internal and triggered pulse modulation. TTL-level compatible, nominal source impedance 50 Ω .
Data clock input	Accepts a data clock signal to synchronize serial data for use with internal baseband generator (Option 602). Maximum rate 50 MHz. Damage levels are $> +5.5$ V and < -0.5 V.
Data input	Accepts serial data for use with internal baseband generator (Option 602). Maximum rate 50 Mb/s. Data must be valid on the falling edges of data clock (normal mode) or the symbol sync (symbol mode). Damage levels are $> +5.5$ V and < -0.5 V.
I input	Accepts an "I" input either for I/Q modulation or for wideband AM. Nominal input impedance 50 or 600 Ω . Damage levels are 1 V_{rms} and 5 V_{peak} .
Q input	Accepts a "Q" input for I/Q modulation. Nominal input impedance 50 or 600 Ω . Damage levels are 1 V_{rms} and 5 V_{peak} .
Symbol sync input	Accepts symbol sync signal for use with internal baseband generator (Option 602). Symbol sync might occur once per symbol or be a single, one bit wide pulse to synchronize the first bit of the first symbol. Maximum rate 50 MHz. Damage levels are $> +5.5$ V and < -0.5 V.

1. Digital inputs and outputs are 3.3 V CMOS unless indicated otherwise. Inputs will accept 5 V CMOS, 3 V CMOS or TTL voltage levels.

Rear panel connectors

(All connectors are BNC female unless otherwise noted.)¹

Auxiliary interface (Dual mode)	Used for RS-232 serial communication and for master/slave source synchronization. (9-pin D-subminiature female connector) For master/slave operation, use Agilent part number 8120-8806 master/slave interface cable.
 GPIB	Allows communication with compatible devices
 LAN	Allows 10baseT LAN communication
 10 MHz input	Accepts a 10 MHz external reference (timebase) input. Nominal input impedance 50 Ω. Damage levels > +10 dBm.
 10 MHz output	Outputs internal or external reference signal. Nominal output impedance 50 Ω. Nominal output power +4 dBm.
 Sweep output (Dual mode)	Supplies a voltage proportional to the RF power or frequency sweep ranging from 0 volts at the start of sweep to +10 volts (nom) at the end of sweep, regardless of sweep width. During CW operation, supplies a voltage proportional to the output frequency, +10 volts (nom) corresponding to the maximum specified frequency. When connected to an Agilent 8757D scalar network analyzer (Option 007), generates a selectable number of equally spaced 1 μs pulses (nom) across a ramp (analog) sweep. Number of pulses can be set from 101 to 1601 by remote control from the 8757D. Output impedance: < 1 Ω (nom), can drive 2000 Ω.
 Stop sweep In/Out	Open-collector, TTL-compatible input/output. In ramp sweep operation, provides low level (nominally 0 V) during sweep retrace and bandcross intervals, and high level during the forward portion of the sweep. Sweep will stop when grounded externally; sweep will resume when allowed to go high.
 Trigger output (dual mode)	Outputs a TTL signal. High at start of dwell, or when waiting for point trigger; low when dwell is over or point trigger is received. In ramp sweep mode, provides 1601 equally-spaced 1 μs pulses (nom) across a ramp sweep. When using LF out, provides 2 μs pulse at start of LF sweep.
 Trigger input	Accepts 3.3 V CMOS signal for triggering point-to-point in manual sweep mode, or to trigger start of LF sweep. Damage levels ≥ +10 V or ≤ -4 V.
 Source module interface	Provides bias, flatness correction, and leveling connections to the Agilent model 83550 Series mm-wave source modules.
 Source settled	Provides an output trigger that indicates when the signal generator has settled to a new frequency or power level. High indicates source not settled, low indicates source settled.
 Z-axis Blank/Markers	During ramp sweep, supplies + 5 V (nom) level during retrace and bandswitch intervals. Supplies - 5 V (nom) level when the RF frequency is at a marker frequency.
 10 MHz EFC	(Option UNX only) Accepts an external DC voltage, ranging from -5V to +5V, for electronic frequency control (EFC) of the internal 10 MHz reference oscillator. This voltage inversely tunes the oscillator about its center frequency approximately -0.07 ppm/V. The nominal input impedance is greater than 1 MΩ
 .25 – 3.2 GHz coherent carrier output	Outputs RF signal modulated with FM or ΦM but not I/Q, AM or pulse. Nominal power 0 dBm. Frequency range from 250 MHz to 3.2 GHz. Not useful for output frequency > 3.2 GHz. Damage levels 20 V _{DC} and 13 dBm reverse RF power. (SMA female).

1. Digital inputs and outputs are 3.3 V CMOS unless indicated otherwise. Inputs will accept 5 V CMOS, 3 V CMOS or TTL voltage levels.

Baseband generator clock input	Accepts a sine or square wave PECL clock input with a frequency range of 200 to 400 MHz (resulting in sample rates of 50 MSa/s to 100 MSa/s). The recommended input level is approximately $1 V_{\text{peak-to-peak}}$ for a square wave and 0 dBm to 6 dBm for a sine wave. Allows the baseband generators of multiple signal sources to run off same clock.
Burst gate input	Accepts signal for gating burst power for use with internal baseband generator (Option 602). The burst gating is used when you are externally supplying data and clock information. The input signal must be synchronized with the external data input that will be output during the burst. The burst power envelope and modulated data are internally delayed and re-synchronized. The input signal must be CMOS high for normal burst RF power or CW RF output power and CMOS low for RF off. Damage levels are $> +5.5 V$ and $< -0.5 V$.
Event 1 output	In real-time mode, outputs a pattern or frame synchronization pulse for triggering or gating external equipment, for use with internal baseband generator (Option 602). May be set to start at the beginning of a pattern, frame, or timeslot and is adjustable to within \pm one timeslot with one bit resolution. In arbitrary waveform mode, outputs a timing signal generated by marker 1.
Event 2 output	In real-time mode, outputs a data enable signal for gating external equipment, for use with internal baseband generator (Option 602). Applicable when external data is clocked into internally generated timeslots. Data is enabled when signal is low. In arbitrary waveform mode, outputs a timing signal generated by marker 2.
I and Q outputs	Outputs the analog I/Q modulation signals from the internal baseband generator. Nominal output impedance 50Ω , DC-coupled. Damage levels $\pm 3.5 V$.
I and Q outputs	Outputs the complement of the I and Q signals for differential applications. Nominal output impedance 50Ω , DC-coupled. Damage levels $\pm 3.5 V$.
Pattern trigger input	Accepts signal to trigger internal pattern or frame generator to start single pattern output, for use with internal baseband generator (Option 602). Minimum pulse width 100 ns. Damage levels are $> +5.5 V$ and $< -0.5 V$.
Wideband I and Q inputs	Direct differential high-bandwidth analog inputs to I/Q modulator in 3.2 to 44 GHz range and useable for carriers $< 3.2 GHz$. Not calibrated. 0 dBm maximum. (Option 016 only).
Removable flash memory drive	Accepts 8 GB compact flash memory card for optional non-volatile memory (Option 009 only). All user information (save/recall settings, flatness files, presets, etc.) is stored on removable memory card when Option 009 is installed.
Alternate power input	Accepts CMOS signal for synchronization of external data and alternate power signal timing. Damage levels are $> +8 V$ and $< -4V$.
Data clock output Data output	Relays a CMOS bit clock signal for synchronizing serial data. Outputs data from the internal data generator or the externally supplied signal at data input. CMOS signal.
Event 3 output	In arbitrary waveform mode, outputs a timing signal generated by marker 3. Damage levels $> +8 V$ and $< 4 V$.
Event 4 output	In arbitrary waveform mode, outputs a timing signal generated by marker 4. Damage levels $> +8 V$ and $< 4 V$.
Symbol sync output	Outputs CMOS symbol clock for symbol synchronization, one data clock period wide.

Auxiliary I/O connector
(37-pin) used with Option 602

Options, Accessories, and Related Products

Model/option	Description
E8267D-520	Frequency range from 250 kHz to 20 GHz
E8267D-532	Frequency range from 250 kHz to 31.8 GHz
E8267D-544	Frequency range from 250 kHz to 44 GHz
E8267D-602	Internal baseband generator, 64 MSa memory
E8267D-003	PSG digital output connectivity with N5102A
E8267D-004	PSG digital input connectivity with N5102A
E8267D-007	Analog ramp sweep
E8267D-009 ²	8 GB removable flash memory
E8267D-016	Wideband external I/Q inputs
E8267D-403	Calibrated AWGN
E8267D-409	Global Positioning System (GPS) personality
E8267D-422	Scenario generator for GPS personality
E8267D-UNX	Ultra low phase noise
E8267D-UNT	AM, FM, phase modulation, and LF output
E8267D-UNU	Pulse modulation
E8267D-UNW	Narrow pulse modulation
E8267D-1ED	Type-N (f) RF output connector
E8267D-1EH	Improved harmonics below 2 GHz
E8267D-1EM	Moves all front panel connectors to the rear panel
E8267D-1CN	Front handle kit
E8267D-1CM	Rackmount flange kit
E8267D-1CP	Rackmount flange and front handle kit
E8267D-UK6	Commercial calibration certificate and test data
E8267D-CD1	CD-ROM containing the English documentation set
E8267D-ABA	Printed copy of the English documentation set
E8267D-0BW	Printed copy of the assembly-level service guide
E8267D-SP2	Dynamic sequencing capability
Application Software	
E8267D-SP1	Signal Studio for jitter injection
N7600B	Signal Studio for 3GPP W-CDMA FDD
N7601B	Signal Studio for 3GPP2 CDMA
N7602B	Signal Studio for GSM/Edge
N7606A	Signal Studio for Bluetooth
N7613A	Signal Studio for 802.16-2004 Fixed WiMax
N7615B	Signal Studio for 802.16 OFDMA mobile WiMax
N7617B	Signal Studio for 802.11 WLAN
N7619A	Signal Studio for Multiband OFDM UWB
N7620A	Signal Studio for pulse building
N7621B	Signal Studio for multitone distortion testing
N7622A	Signal Studio Toolkit
N7623B	Signal Studio for digital video
Special Options	
E8267D-H1S	1 GHz external frequency reference input
E8267D-H1G	Connections for phase coherency and improved phase stability < 250 MHz
E8267D-HCC	Connections for phase coherency > 250 MHz ¹
E8267D-H18	Wideband downconverter
Accessories	
Z5623A-Kxx	Distribution network (lock box) ¹
1819-0427	8 GByte compact flash memory card
8120-8806	Master/slave interface cable
N5102A	Digital signal interface module
N5101A	Baseband Studio PCI card

1. Utilized for multiple source phase coherency applications.

2. Option 009 applies to units with serial numbers ending with 48290000 or greater. For units with lower serial numbers, refer to the data sheet shipped with the unit or the version of this document dated January 15, 2008.

Web Resources

For additional product information, visit:

www.agilent.com/find/psg

For information about renting, leasing or financing Agilent's latest technology, visit:

www.agilent.com/find/buy/alternatives

For accessory information, visit:

www.agilent.com/find/accessories

For additional description of Agilent's IO Libraries Suite features and installation requirements, please go to:

www.agilent.com/find/iosuite/database

Related Agilent Literature

E8267D PSG Vector Signal Generator

Configuration Guide, Literature number 5989-1326EN

E8257D PSG Analog Signal Generator

Data Sheet, Literature number 5989-0698EN

E8663D PSG RF Analog Signal Generator

Data Sheet, Literature number 5990-4136EN

PSG Two-tone and Multitone Personalities

Application Note AN 1410, Literature number 5988-7689EN

Signal Studio for Pulse Building

Technical Overview, <http://wireless.agilent.com/wireless/helpfiles/n7620a/n7620a.htm>

Signal Studio for Multitone Distortion

Technical Overview, <http://wireless.agilent.com/wireless/helpfiles/n7621/n7621.htm>

Agilent I/Q Modulation Considerations for PSG Vector Signal Generators

Application Note, Literature number 5989-7057EN

Baseband Studio Digital Signal Interface Module

Technical Overview, Literature number 5988-9495EN

Security Features of Agilent Technologies Signal Generators

Part Number E4400- 90621



Agilent Email Updates

www.agilent.com/find/emailupdates

Get the latest information on the products and applications you select.



www.lxistandard.org

LXI is the LAN-based successor to GPIB, providing faster, more efficient connectivity. Agilent is a founding member of the LXI consortium.

Agilent Channel Partners

www.agilent.com/find/channelpartners

Get the best of both worlds: Agilent's measurement expertise and product breadth, combined with channel partner convenience.

Remove all doubt

Our repair and calibration services will get your equipment back to you, performing like new, when promised. You will get full value out of your Agilent equipment through-out its lifetime. Your equipment will be serviced by Agilent-trained technicians using the latest factory calibration procedures, automated repair diagnostics and genuine parts. You will always have the utmost confidence in your measurements. For information regarding self maintenance of this product, please contact your Agilent office.

Agilent offers a wide range of additional expert test and measurement services for your equipment, including initial start-up assistance, onsite education and training, as well as design, system integration, and project management.

For more information on repair and calibration services, go to:

www.agilent.com/find/removealldoubt

www.agilent.com

For more information on Agilent Technologies' products, applications or services, please contact your local Agilent office. The complete list is available at:

www.agilent.com/find/contactus

Americas

Canada	(877) 894-4414
Latin America	305 269 7500
United States	(800) 829-4444

Asia Pacific

Australia	1 800 629 485
China	800 810 0189
Hong Kong	800 938 693
India	1 800 112 929
Japan	0120 (421) 345
Korea	080 769 0800
Malaysia	1 800 888 848
Singapore	1 800 375 8100
Taiwan	0800 047 866
Thailand	1 800 226 008

Europe & Middle East

Austria	43 (0) 1 360 277 1571
Belgium	32 (0) 2 404 93 40
Denmark	45 70 13 15 15
Finland	358 (0) 10 855 2100
France	0825 010 700*
Germany	49 (0) 7031 464 6333
Ireland	1890 924 204
Israel	972-3-9288-504/544
Italy	39 02 92 60 8484
Netherlands	31 (0) 20 547 2111
Spain	34 (91) 631 3300
Sweden	0200-88 22 55
Switzerland	0800 80 53 53
United Kingdom	44 (0) 118 9276201

Other European Countries:
www.agilent.com/find/contactus

Revised: October 1, 2009

Product specifications and descriptions in this document subject to change without notice.

© Agilent Technologies, Inc. 2010
Printed in USA, May 24, 2010
5989-0697EN



Agilent Technologies