

UCS 500N5

MULTIFUNCTIONAL TESTGENERATOR FOR TRANSIENTS (EFT/BURST, SURGE & POWER FAIL) UP TO 5.5KV



FOR TESTS ACCORDING TO ...

- > EN 300329
- > EN 300340
- > EN 300342-1
- > EN 300386 V1.3.2
- > EN 301489-1
- > EN 301489-17
- > EN 301489-24
- > EN 301489-7
- > EN 50121
- > EN 55024
- > EN 61000-4-11
- > EN 61000-4-29
- > EN 61000-4-4
- > EN 61000-4-5
- > EN 61000-4-8
- > EN 61000-4-9
- > EN 61000-6-1
- > EN 61000-6-2
- > FCC 97-270 (part 68)
- > IEC 60255-22-5
- > IEC 61000-4-11
- > ...

UCS 500N5 - COMPACT TESTER FOR EFT/BURST, SURGE AND POWER FAIL








The UCS 500N5 ultra-compact simulator is the most versatile tester to cover transient and power fail requirements according to international standards (basic and generic standards) and product/product family standards. The UCS 500N5 is the most economic solution for tests during development as well as for full-compliant immunity tests and CE Marking for single phase DUT with the ability to be extended for testing three-phase DUTs by means of an automatically controlled external coupling network up to 100A.

EM TEST supplies a large range of accessories for the various applications such as magnetic field tests.

HIGHLIGHTS

- > **Burst module (IEC/EN 61000-4-4) up to 5.5kV**
- > **Surge module (IEC/EN 61000-4-5) up to 5kV**
- > **PowerFail module (IEC/EN 61000-4-11)**
- > **Magnetic field tests with optional accessoires**
- > **Built-in single phase coupler 300V/16A**
- > **Manual operation from front panel**
- > **USB and GPIB-Bus for remote control**

APPLICATION AREAS

- | | |
|---|--|
|  INDUSTRY |  COMPONENTS |
|  MEDICAL |  BROADCAST |
|  RESIDENTIAL |  RENEWABLE ENERGY |
|  TELECOM | |

TECHNICAL DETAILS

BENEFITS

ALL IN ONE - ALL WHAT YOU NEED FOR YOUR TESTS

The UCS 500N5 includes everything necessary to conduct fully compliant tests. The power mains supply for the controls and for the DUT is separate to render it more flexible to use with different DUT supply voltages. The UCS 500N5 can be operated manually from the front panel or by remote via the built-in USB or GPIB interface. Fail inputs allow to control an ongoing test sequence based on the status of the DUT. Monitoring outputs (BNC) are offered for easy signal measurement and verification. Safety features such as interlock and warning lamp control are available. Pre-programmed Standard Test routines allow highest user convenience. Still the UCS 500N5 offers the Quick Start test routine where parameters can be changed on-line during the test to evaluate the susceptibility level of an individual DUT.

OPERATION

EASY TO OPERATE

Front panel menu and function keys enable the user to program his test routines quickly and accurately. The cursor allows fast control of all test parameters of the programmed routine, thus test procedures are simplified and confidence is generated that every step is carried out correctly.



SOFTWARE

IEC.CONTROL SOFTWARE FOR CONTROL AND DOCUMENTATION

Outstanding user convenience, clearly structured windows and operation features and the EM TEST standards library along with the flexibility to generate user specific test sequences very easily are the main features of iec.control software. The software is automatically configured according to the connected EM TEST generators. Extensive reporting capabilities help the user to create test reports that meet international requirements.

iec.control is supported by Windows 2000, Windows XP, Windows Vista and Windows 7. Remote control is achieved either via USB or GPIB. iec.control supports a wide range of GPIB cards of National Instruments.

OTHER MODELS

UCS 500N SERIES - COMPACT TESTERS UP TO 7KV

The UCS 500N ultra-compact testers for EFT/burst, Surge and Power Fail are available in two different models; with voltage capability up to 5.5kV or up to 7kV.

TECHNICAL DETAILS

AUXILIARY DEVICES

CNI 503 - 3PHASE COUPLING/DECOUPLING NETWORKS FOR BURST AND SURGE

EM TEST offers a range of fully automatic 3-phase coupling/decoupling networks for burst and surge to extend the test capability for three-phase DUTs. The networks have a rated current of up to 100A.

MV 2616 - MOTORISED VARIAC FOR VOLTAGE VARIATION

A motorised variac is offered as an alternative to the tapped autotransformers for voltage dips/interruptions and voltage variation tests as per IEC 61000-4-11. The motorised variac can also be used for automated magnetic field tests.

V 4780 - TAPPED VOLTAGE TRANSFORMER FOR VOLTAGE DIPS AND INTERRUPTIONS

The V 4780 tapped autotransformer is designed to supply the required voltages as per IEC 61000-4-11 Ed.2:2004 to perform voltage dips and interruptions.

V 4780S2 - TAPPED VOLTAGE TRANSFORMER FOR VOLTAGE DIPS AND INTERRUPTIONS

The V 4780S2 tapped autotransformer is designed to supply the required voltages as per IEC 61000-4-11 Ed.2:2004 to perform voltage dips and interruptions. Compared to the manually operated V 4780 the V 4780S2 model offers automatic change of taps according to the selected voltage level.

CNV 504N/508N - SURGE COUPLING/DECOUPLING NETWORKS FOR SIGNAL/DATA LINES

CNV 504N/508N coupling/decoupling networks are available to perform surge tests on I/O lines, signal/data lines and telecom lines as per IEC 61000-4-5.

ACCESSORIES

MS 100N - MAGNETIC FIELD COIL FOR POWER-FREQUENCY AND PULSED MAGNETIC FIELDS

The MS 100N is a 1sqm magnetic field coil as specified in IEC/EN 61000-4-8 and IEC/EN 61000-4-9. Its design allows easy moving of the coil. The field coil is adjustable in height and allows for 360degr rotation.

To generate power-frequency magnetic fields in the lower range the current transformer MC 2630 is used while high-field strength above 100A/m requires the MC 26100 current transformer.

HFK - CAPACITIVE COUPLING CLAMP

The HFK is a fully compliant capacitive coupling clamp as per specification of IEC 61000-4-4.

ITP - IMMUNITY TEST PROBES

ITP is a tool being used for development test. It consists of a variety of electrical field probes. The probes allow to locate weak points within a system or on a PCB. The burst pulse is used to generate the disturbance signal.

CA EFT KIT - VERIFICATION KIT FOR EFT/BURST PULSES

As per IEC 61000-4-4 Ed.2 the characteristic of the burst generator needs to be verified with two different loads, 50ohm and 1,000ohm. EM TEST offers a calibration kit consisting of the two loads and an adapter to verify the pulses at the DUT output.

CA HFK KIT - VERIFICATION KIT FOR CAPACITIVE COUPLING CLAMP

The IEC 61000-4-4 Ed 3.0 published 2012 recommends the calibration of the capacitive coupling clamp into a 50ohm coaxial load.

The capacitive coupling clamp (HFK) is connected to the 50 ohm output of the EFT generator. A flexible insulated plate inside the HFK is connected to a coaxial 50 ohm load resistor for verificate the EFT / Burst wave of the capacitive coupling clamp.

TECHNICAL DETAILS
ELECTRICAL FAST TRANSIENTS
BURST MODULE, EFT/N5

| | |
|------------------|--|
| | As per EN/IEC 61000-4-4 and EN 61000-6-1, -6-2 |
| Test voltage | 200V - 5,500V \pm 10%; 100V - 2,750V \pm 10% into 50ohm |
| Pulse shape | 5/50ns into 50ohm and 1,000ohm |
| Rise time tr | 5ns \pm 30% into 50ohm; 5ns \pm 30% into 1,000ohm |
| Pulse width td | 50ns \pm 30% into 50ohm; 50ns -15/+100ns into 1,000ohm |
| Source impedance | 50ohm |
| Polarity | Positive/negative |

TRIGGER CIRCUIT

| | |
|-------------------|--|
| Trigger of bursts | Automatic, manual, external |
| Synchronization | 0° - 360°, resolution 1° (16 - 500Hz) |
| Burst duration | td = 0.10ms - 999ms |
| Repetition rate | tr = 10ms - 9,999ms |
| Spike frequency | f = 0.1kHz - 1,000kHz |
| Test duration | T = 0:01min - 99:59min T > 99:59min --> endless |

OUTPUTS

| | |
|---------------|---------------------------------------|
| Direct | Via 50ohm coaxial connector |
| Coupling mode | L, N, PE; all combinations |
| DUT supply | AC: 300V/16A; 50/60Hz DC: 300V/16A |
| CRO trigger | 5V trigger signal for oscilloscope |

TEST ROUTINES

| | |
|------------------------|--|
| Quick Start | On-line adjustable parameters, easy-to-use |
| Standard Test routines | As per IEC 61000-4-4, Levels 1 - 4 As per EN 61000-6-1, -6-2 Manual Standard Test routine |
| User Test routines | Synchronous burst release Random burst release Change voltage after T Frequency sweep within one burst Frequency sweep with constant number of pulses Frequency sweep with constant burst duration Change polarity after T |

OPTIONS

| | |
|------------|--|
| HFK | Capacitive coupling clamp as per IEC 61000-4-4 |
| KW50 | 100:1 divider, 50ohm |
| KW1000 | 500:1 divider, 1,000ohm |
| CA EFT kit | Kit for burst pulse verification consisting of KW50, KW1000 and adapter for DUT port in a plastic case for storage |
| A6dB | 6dB attenuator, 50ohm |
| ITP | Immunity test probes (electrical field generation) |
| ITP/H | Immunity test probe (magnetic field generation) |

TECHNICAL DETAILS

COMBINATION WAVE / SURGE

SURGE MODULE, VCS/N5

| | |
|--------------------------|--|
| | As per EN/IEC 61000-4-5 and EN 61000-6-1, -6-2 |
| Voltage (o.c.) | 160V - 5,000V ± 10% |
| Pulse front time | 1.2us ± 30% |
| Pulse time to half value | 50us ± 20% |
| Current (s.c.) | Max. 2,500A ± 10% |
| Pulse front time | 8us ± 20% |
| Pulse time to half value | 20us ± 20% |
| Polarity | Positive/negative/alternating |
| Event counter | 1 - 30,000 or endless, selectable |

TRIGGER CIRCUIT

| | |
|-------------------|-----------------------------|
| Release of pulses | Automatic, manual, external |
| Synchronization | 0° - 360°, resolution 1° |
| Repetition rate | max. 1Hz (1s - 999s) |

OUTPUTS

| | |
|---------------|--|
| Direct | Via HV connectors for external coupling networks (Z _i = 2ohm with optional adapter IMN 2) |
| Coupling mode | Line to line Line(s) to ground |
| DUT supply | AC: 300V/16A; 50/60Hz DC: 300V/16A |
| CRO trigger | 5V trigger signal for oscilloscope |

MEASUREMENTS

| | |
|---------------|---------------------------|
| CRO Ū-monitor | 10Vp at 5,000V |
| CRO Î-monitor | 10Vp at 2,500A |
| Peak voltage | 5,000V in the LCD display |
| Peak current | 2,500A in the LCD display |

TEST ROUTINES

| | |
|------------------------|--|
| Quick Start | One-line adjustable parameters, easy-to-use |
| Standard Test routines | As per IEC 61000-4-5, Levels 1 - 4 As per EN 61000-6-1, -6-2 Manual Standard Test routine |
| User Test routines | Change polarity after n pulses Change coupling after n pulses Change voltage after n pulses Change phase angle after n pulses |
| Pulsed Magnetic Field | as per IEC 61000-4-9 Test levels 100, 300 and 1,000A/m Test level steplessly adjustable under Quick Start |

OPTIONS

| | |
|----------|--|
| CNV504Nx | Coupling network for 4 signal/data lines as per IEC 61000-4-5 |
| CNV508Nx | Coupling network for 8 signal/data lines as per IEC 61000-4-5 |
| IMN 2 | Impedance matching adapter to match direct output to 2ohm source impedance |

TECHNICAL DETAILS

POWER FAIL, DIPS & INTERRUPTIONS, VOLTAGE VARIATIONS

POWER FAIL MODULE, PFS/N5

| | |
|-----------------|--|
| | As per EN/IEC 61000-4-11, IEC/EN 61000-4-29 and EN 61000-6-1, -6-2 |
| Channel PF1/PF2 | AC voltage: max. 300V AC current: max. 16A DC voltage: max. 300V DC current: max. 16A |
| Frequency | 16Hz - 500Hz and DC |
| Switching time | < 5us into a 100ohm resistive load |
| Inrush current | > 500A |
| Protection | Both channels are protected against short-circuit conditions. |

TRIGGER CIRCUIT

| | |
|-------------------|---------------------------------------|
| Trigger of events | Automatic, manual, external |
| Synchronization | 0° - 360°, resolution 1° (16 - 500Hz) |
| Repetition rate | 10ms - 9,999s |
| Event duration | 20us - 9,999s |

OUTPUTS

| | |
|---------------|------------------------------------|
| DUT terminals | L, N and PE |
| CRO trigger | 5V trigger signal for oscilloscope |

MEASUREMENTS

| | |
|-------------|---|
| DUT voltage | In the LCD display |
| DUT current | In the LCD display |
| MON V | Measurement of the DUT voltage; built-in 100:1 divider |
| MON I | Measurement of the DUT current; 10mV/A; max. 1,000A |

TEST ROUTINES

| | |
|------------------------|---|
| Quick Start | On-line adjustable parameters, easy-to-use |
| Standard Test routines | As per EN/IEC 61000-4-11 for AC supplies As per EN/IEC 61000-4-29 for DC supplies As per EN 61000-6-1, -6-2 Manual Standard Test routine |
| User Test routines | Voltage variation, control of an external variac Change phase angle after n events Change event duration after n events Inverse mode |
| 50/60Hz magnetic field | As per EN/IEC 61000-4-8 Test levels 1, 3, 10 and 30A/m with external current transformer MC2630 Test levels 100, 300 and 1,000A/m with external current transformer MC26100 |

OPTIONS

| | |
|----------|--|
| V4780 | Tapped autotransformer as per IEC 61000-4-11 Ed.2 |
| V4780 S2 | Tapped autotransformer as per IEC 61000-4-11 Ed.2 with automatic change of tap |
| MV2616 | Motorised variac (0 - 250V, 16A) |
| MS100N | Magnetic field coil, 1m x 1m |
| MC2630 | Current transformer for magnetic fields up to 30A/m |
| MC26100 | Current transformer for magnetic fields up to 1,000A/m |
| CA PFS | Calibration box for inrush current verification as per IEC 61000-4-11 |

TECHNICAL DETAILS

GENERAL DATA

INTERFACES

| | |
|--------------------|--|
| Serial interface | USB |
| Parallel interface | IEEE 488, addresses 1 - 30 |
| Analog output | 0 - 10VDC to control an external transformer |
| CN interface | 15pin SubD connector to control an external coupling network |
| Fail inputs | DUT monitoring via Fail1 and Fail2 input (one each) |

DIMENSIONS

| | |
|------------|--------------|
| Dimensions | 19", 3HU, |
| Weight | approx. 25kg |

MAINS

| | |
|----------------|--------------------------------------|
| Supply voltage | 115V/230VAC +10%/-15% |
| Power | approx. 75W |
| Frequency | 50/60Hz |
| Fuses | 2 x T 2AT (230V) or 2 x T 4AT (115V) |

SAFETY

| | |
|------------------|---------------------------------|
| Safety standard | EN/IEC 61010 |
| Security circuit | Control input (24VDC) |
| Warning lamp | Floating contact (max. 230V/6A) |

ACCESSORIES INCLUDED

| | |
|--------------|--|
| Mains supply | Plug depends on the country of use |
| DUT supply | Plug depends on the country of use |
| DUT adapter | Socket depends on the country of use |
| | Operation manual, Calibration certificate, iec.control remote control software |

OPTIONS

| | |
|---------------|---|
| CNI 503Ax | 3-phase coupling/decoupling networks as per IEC 61000-4-4 and -4-5 up to 100A per phase |
| iec.control 1 | Remote control and documentation software, including standard test routines and reporting capabilities. |

SPECIAL EQUIPMENT (ON REQUEST)

AVAILABLE MODELS:

| | |
|-------------|---|
| UCS 500N5.1 | Ultra compact simulator with EFT/N5 up to 5.5kV, VCS/N5 up to 5kV and PFS/5; 1ph CDN 300V AC/DC (p-n) / 32A |
| UCS 500N5.2 | Ultra compact simulator with EFT/N5, VCS/N5 and PFS/N5; 1ph CDN 400V AC/DC (p-n) / 16A |
| UCS 500N5.3 | Ultra compact simulator with EFT/5, VCS/5 and PFS/N5; 1ph CDN 400VAC (L-N) / 32A |
| UCS 500N5.7 | Ultra compact simulator with EFT/N5 and VCS/N5; 1ph CDN 300V (p-n) / 16A (but without PFS module) |
| UCS 500N5.8 | Ultra compact simulator for EFT/N5 and PFS/N5; 1ph CDN 300V AC/DC (p-n) / 16A |

COMPETENCE WHEREVER YOU ARE



CONTACT EM TEST DIRECTLY

Switzerland

EM TEST (Switzerland) GmbH › Sternenhofstraße 15 › 4153 Reinach › Switzerland
 Phone +41 (0)61/7179191 › Fax +41 (0)61/7179199
 Internet: www.emtest.ch › E-mail: sales.emtest@ametek.com

Germany

EM TEST GmbH › Lünener Straße 211 › 59174 Kamen › Deutschland
 Phone +49 (0)2307/26070-0 › Fax +49 (0)2307/17050
 Internet: www.emtest.com › E-mail: info.emtest@ametek.de

France

EM TEST FRANCE › Le Trident - Parc des Collines › Immeuble B1 - Etage 3 › 36, rue Paul Cézanne › 68200 Mulhouse › France
 Phone +33 (0)389 31 23 50 › Fax +33 (0)389 31 23 55
 Internet: www.emtest.fr › E-mail: info@emtest.fr

Poland

EM TEST Polska › ul. Ogrodowa 31/35, 00-893 Warszawa › Polska
 Phone +48 (0)518 64 35 12
 Internet: www.emtest.com/pl › E-mail: info_polska.emtest@ametek.de

USA / Canada

EM TEST USA › 9250 Brown Deer Road › San Diego › CA 92121
 Phone +1 (303) 693-1778
 Internet: www.emtest.com › E-mail: sales.emtest@ametek.com

P.R. China

E & S Test Technology Limited › Rm 913, Leftbank › No. 68 Bei Si Huan Xi Lu › Haidian District › Beijing 100080 › P.R. China
 Phone +86 (0)10 82 67 60 27 › Fax +86 (0)10 82 67 62 38
 Internet: www.emtest.com › E-mail: info@emtest.com.cn

Republic of Korea

EM TEST Korea Limited › #405 › WooYeon Plaza › #986-8 › YoungDeok-dong › Giheung-gu › Yongin-si › Gyeonggi-do › Korea
 Phone +82 (31) 216 8616 › Fax +82 (31) 216 8616
 Internet: www.emtest.co.kr › E-mail: sales@emtest.co.kr

Information about scope of delivery, visual design and technical data correspond with the state of development at time of release. Technical data subject to change without further notice.