



rf/microwave instrumentation

Model FM7004 Field Monitor M1 through M4 0.4-1000 V/m 12.0 mA/m-17 A/m Sensitivity

The AR RF/Microwave Instrumentation Model FM7004 is a versatile electric and magnetic field monitoring system which performs all measurement display and control functions for field related testing. The FM7004 accepts inputs from up to 4 isotropic Field Probes which are all sold separately to match the test application.

The FM7004 field monitor provides four digital interfaces (IEEE-488, USB, RS-232, and Ethernet) and a highly readable, user configurable, graphic Liquid Crystal Display. The monitor is menu driven and can be controlled from the front panel or remotely through any of the interfaces. The FM7004 displays up to four probe readings simultaneously, in any combination of the "E" field or "H" field 7000 series probes. Readings from each axis, plus the composite reading, are displayed simultaneously. The FM7004 recognizes each attached 7000 series probe (FP, FH, FL) and automatically displays the proper decimal places and units. Any faults that occur will be logged and the unit is programmed to be self correcting when possible. As a software driven instrument, field monitor software upgrades can be made through the USB port.



The isotropic field probes, have an integral optical transceiver which communicates with the field monitor through a twin fiber optic cable. The operator can select minimum, maximum or average reading from any or all selected probes thus enjoying complete flexibility in choice of signal input. Peak hold capability has also been incorporated with local or remote controlled start and stop.

The FM7004 has the ability to correct probe readings over frequency using a set of correction factors stored in its internal memory. The FM7004 allows for up to six tables of field probe correction factors to be stored. One table of correction factors can contain up to 30 different frequency points. The tables are loaded on the FM7004 using the USB port and the Table Loader program.

MAIN		CHAN
CH2	V/M	
108.54		DISP
99.31	X	SYST
42.37	Y	
11.05	Z	

Single Probe X,Y,Z Display
Min/Max/Average Display

MAIN				CHAN
MIN	V/M	MAX	V/M	
17.43		120.57		DISP
AVG	V/M			SYST
100.57		CH1 XYZ		
		CH2 XYZ		
		CH3 XYZ		
		CH4 XYZ		

MAIN					CHAN
CH1	V/M	CH2	V/M		
31.93		350.39		DISP	
14.92	X	350.04	X		
15.27	Y	3.75	Y		
23.74	Z	15.20	Z		
CH3	V/M	CH4	V/M	SYST	
2.70		190.85			
0.78	X	10.08	X		
1.07	Y	19.80	Y		
2.35	Z	189.56	Z		

DISPLAY MODES

Multi-probe X,Y,Z Display
Min/Max Hold Display

MIN MAX HOLD				RUN CLR
MIN	V/M	MAX	V/M	
0.63		462.87		STOP
		CH1 XYZ		
		CH2 XYZ		
		CH3 XYZ		
		CH4 XYZ		

SPECIFICATIONS

Sensitivity	0.4–1000 V/m (probe dependent) 12.0 mA/m–17 A/m (probe dependent)
Frequency response	100 kHz - 60 GHz (probe dependent)
Inputs	Up to 4 independent probes, through 4 F/O FSMA pairs
Overload withstand	Probe dependent
Output	graphical, color LCD digital display, resolution 0.01 IEEE-488 interface USB 2.0 (test and measurement class) RS-232 interface Ethernet
Sample Rate	1-60 Samples/sec. (probe dependent)
Power requirements	
Input voltage	Universal input 90 - 260 VAC, 50-60 Hz
Input current	0.2 - 0.6 Amps
Input type	IEC Inlet with filter
Fuse	1A, 5x20 mm slow blow
Operating temperature range.....	10 - 40° C (50 - 104° F) @ 5 - 95% RH non-condensing
Enclosure.....	Desktop case, 2U high
Correction factor tables	
Number of tables	Stores up to 6 different tables (each table corresponding to one probe)
Frequency points per table.....	2 to 30
Weight	
without enclosure	2.3 kg (5 lb)
with enclosure	6.7 kg (14.75 lb)
Size (WxHxD)	
without enclosure	48.3 x 9.0 x 25.4 cm (9 x 3.5 x 10 in)
with enclosure	49.8 x 12.7 x 30.5 cm (19.6 x 5.0 x 12.0 in)

MODEL	DESCRIPTION
FM7004	Housed in a 2U instrument case
FM7004M1	Rack mount (Instrument case removed)
FM7004M2	Housed in a 3U instrument case to allow for one FI7000 to be installed
FM7004M3	Housed in a 4U instrument case to allow for two FI7000's to be installed
FM7004M4	Housed in a 6U instrument case to allow for four FI7000's to be installed