

## Magnetic Field Probes

### Agilent 11940A and 11941A Close Field Probes

These hand-held probes are specially designed to measure magnetic field radiation from surface currents, slots, cables, and ICs for EMC diagnostic and troubleshooting measurements. Their unique design results in a high level of electric field rejection. This significantly reduces errors allowing calibrated and repeatable measurements. Each probe is calibrated and comes with a two-meter, RG-223 coaxial cable, an SMA(f) to Type-N(m) adapter, and an SMA(f) to BNC(m) adapter.



<b>Frequency Range</b>	11940A: 30 MHz–1 GHz 11941A: 9 kHz–30 MHz
<b>Maximum Input Power</b>	0.5 W
<b>Temperature Range</b>	Variation over 0° C to + 40° C
<b>Dielectric Breakdown Connector</b>	± 1 dB, typical SMA, replaceable barrel
<b>VSWR</b>	< 3 : 1, typical for 11940A only
<b>Antenna Factor Accuracy</b>	Individually calibrated to within ± 2 dB in a 377 Ω field impedance

### Agilent 11945A Close Field Probe Set

The 11945A close field probe set includes both the 11940A and 11941A probes to provide full coverage from 9 kHz to 1 GHz. This set provides a powerful measurement tool for electrical and mechanical designers who want to search for and eliminate sources of interference from their products early in the design process. Option E51 adds the 8447F Option H64 dual preamplifier, a 36 inch (914 mm) Type-N cable and a carrying bag to store and protect the entire set of probes, preamplifier, and cables.

