



Signal Generation

Specifications in brief

Frequency

Range	SME02/03	5 kHz to 1.5/3 GHz
	SME03E/06	5 kHz to 2.2/6 GHz
Resolution		0.1 Hz
Setting time		<10 ms
after IEC/IEEE-bus delimiter		<500 µs
after trigger pulse in list mode		adjustable in steps of 1°
Phase offset		

Reference frequency

Aging (after 30 days of operation)	standard 1 x 10 ⁻⁶ /year	option SM-B1 <1 x 10 ⁻⁹ /day
Temperature effect (0 to 55°C)	2 x 10 ⁻⁶	<5 x 10 ⁻⁸

Spectral purity

Spurious signals	
Harmonics	<-30 dBc, <-26 dBc with SM-B3/B8/B9
Nonharmonics at	
>5 kHz from carrier, f <1.5 GHz	<-80 dBc
SSB phase noise at 20 kHz from carrier, 1 Hz bandwidth,	
FM/φM deviation	<5% of max. deviation
<93.75 125 250 MHz 0.5	1 2 3 6 GHz
<-129 <-140 <-137 <-132	<-126 <-120 <-116 <-116 dBc
Residual FM, rms (f=1 GHz)	
0.3 to 3 kHz (CCITT)	<1 Hz
0.03 to 20 kHz	<4 Hz

Level

Resolution	-144 to +13 dBm
Accuracy for levels >-127 dBm	0.1 dB
f <1.5 GHz	±1 dB
f >1.5 GHz	±1.5 dB
f >3 GHz	±2 dB
Level frequency response at 0 dBm	1 dB, typ. 0.3 dB

Overload protection

protects the unit from externally applied RF power (50 Ω source) and DC voltage, SME02 and 03: ≤50 W/35 V; SME06: ≤1 W/0 V

Simultaneous modulation

any combination of AM, FM (φM), pulse modulation and DM [DM = FSK, 4FSK, FFSK, GFSK, GMSK or QPSK]

Frequency modulation

Operating modes	with option SM-B5 internal, external AC/DC, two-tone with two separate channels FM1 and FM2
Maximum deviation	depending on carrier frequency: 500 kHz (<130 MHz) to 4 MHz (6 GHz) <3% of reading + 20 Hz
Setting error at AF=1 kHz	<0.5%, typ. 0.05%
FM distortion at AF=1 kHz	DC to 500 kHz
and 50% of max. deviation	DC to 2 MHz
Modulation frequency range	depending on carrier frequency: <50 Hz (f _c <93.75 MHz) to <100/200 Hz (f _c 1.5/3 GHz)
for maximum deviation	+1% of deviation
for <25% of max. deviation	
Carrier frequency offset with FM	

Phase modulation

Operating modes	with option SM-B5 internal, external AC/DC, two-tone with two separate channels φM1 and φM2
Maximum deviation	depending on carrier frequency: 5 rad (f _c <130 MHz) to 40 rad (f _c 6 GHz) <3% of reading + 0.01 rad
Setting error at AF=1 kHz	<1%
Distortion at AF=1 kHz and	DC to 100 kHz
50% of max. deviation	
Modulation frequency range	

Digital modulation

Modulation modes	with option SME-B11, standard in SME03E FSK, 4FSK, FFSK, GFSK, GMSK, QPSK, π/4 DQPSK
------------------	---

Operating modes
Internal data generator

internal, external
programming of data, level switching
and burst output

3 x 8192 bit

Storage capacity

same as reference frequency

Frequency accuracy

selectable lengths: 2⁹-1, 2¹⁵-1,

2²⁰-1, 2²¹-1 or 2²³-1

to Cityruf, POCSAG, FLEX specs

4/4.5/4.8 kHz

Data rate, filtered
unfiltered

0.01 to 400 kHz, maximum shift
depending on carrier frequency

0.05 to 90 kbit/s

0.05 to 1900 kbit/s

FFSK

to Cityruf, POCSAG specifications

Shift, filtered

1.5/2/3/3.5/4/4.5 kHz

unfiltered

0.05 to 90 kbit/s

4FSK

to APCO25, ERMES, FLEX,

MODACOM specifications

0.01 to 400 kHz, maximum shift

depending on carrier frequency

1 to 24.3/27 to 48.6 kbit/s

GFSK

to CT2, CT3, DECT specifications

Shift

18/160/288 kHz as well as non-

standard shifts

10 to 585/640 to 1170 kbit/s

to CDPD, GSM1800, DSRR, GSM,

MC9, MD24 to MD192,

MOBITEX8000 specifications

2.4/3.6/4.4.8/6/8/9.6/10/12/

16/19.2/270.833/1000 kbit/s

QPSK, π/4 DQPSK

to APCO25, MSAT, NADC, PDC,

TETRA, TTS specifications

not specified

for f >3 GHz

1 to 24.3/27 to 48.6 kbit/s

Data rate

√cos0.35/0.4/0.5/0.6

Filter

cos0.2/0.35/0.4/0.5/0.6

Amplitude modulation, pulse modulation, internal modulation generator, LF generator, multifunction generator, stereo multiplex signal, VOR modulation signal, ILS modulation signal, pulse generator and sweep see SMT, page 210

List mode

(not SME03E)

automatic, single-shot, manual,

externally triggered

2000

Step time

1 ms to 1 s

Remote control

Command set

IEC 625 (IEEE 488)

General data

Power supply

90 to 132/180 to 265 V,

47 to 440 Hz, autotesting to AC voltage, max. 300 VA

435 mm x 192 mm x 460 mm

Weight

25 kg for fully equipped unit

Ordering information

Signal Generator	SME02	1038.6002.02
	SME03	1038.6002.03
	SME03E	1038.6002.13
	SME06	1038.6002.06

Options

Reference Oscillator OCXO	SM-B1	1036.7599.02
LF Generator	SM-B2	1036.7947.02
Pulse Modulator for SME02	SM-B3	1036.6340.02
for SME03	SM-B8	1036.6805.02
for SME06	SM-B9	1039.5100.02
Pulse Generator (only in combination with SM-B3, SM-B8 or SM-B9)	SM-B4	1036.9310.02
FM/φM Modulator	SM-B5	1036.8489.02
Multifunction Generator	SM-B6	1036.7760.02
DM Coder	SME-B11	1036.8720.02
DM Memory Extension (8 Mbit)	SME-B12	1039.4090.02
FLEX Protocol	SME-B41	1039.5645.02
POCSAG Protocol	SME-B42	1039.5745.02
Rear Connectors for RF and LF	SME-B19	1039.3907.02



[Contents Overview](#)

[Chapter Overview](#)

[Type Index](#)

[R&S Addresses](#)

