

Probe Power Supply

1103



► 1103. 1103 TEKPROBE Power Supply.

TEKPROBE™ BNC Interface

The 1103 is an accessory power supply that provides external power to TEKPROBE BNC Interface probes. The 1103 allows customers to use probes requiring TEKPROBE interface power with any oscilloscope or digitizer that does not provide TEKPROBE BNC power.

The 1103 offers two independently controlled channels consisting of a TEKPROBE BNC interface input, a voltage offset control (providing variable offset or no offset) and BNC signal output.

The offset control supplies a voltage, adjustable via the front panel control. This offset control is available for TEKPROBE BNC probes with this capability. These include: P6203, P6204, P6217, P6231, P6245, P6246, P6247, P6248, P6249 and P6330.

► Characteristics

Output Voltage $\pm 2\%$ – +15 V, -15 V, +5 V, -5 V

Output Current – 300 mA

Outputs – Pin 1: n.c.

Pin 2: n.c.

Pin 3: +5 V

Pin 4: +15 V

Pin 5: Offset ± 1 V

Pin 6: -5 V

Pin 7: -15 V

Power Consumption – ≤ 35 W

Physical Characteristics

	cm	in
Depth	17.8	7
Width	15.8	6.2
Height	8.9	3.9
Weight	kg	lb
Net 1.8	3.9	

*The characteristics for TEKPROBE BNC Interface probes are subject to change when used with the 1103 TEKPROBE Power Supply. Bandwidth, Rise-time, Propagation Delays will generally differ from the advertised probe only specification. These are dependent upon: 1) the cable length from the output BNC connector to the oscilloscope input, 2) the instrumentation input impedance the output BNC is being connected to, and 3) any additional adapters required to properly interface to the test instrumentation.

To use TEKPROBE BNC Interface probes on the 11800, CSA800, TDS8000, CSA8000 or any non-TEKPROBE BNC Interface test instrumentation requires an 1103 TEKPROBE Power Supply, an SMA Male to BNC Female adapter, a 50 Ω BNC cable and if required a 50 Ω feedthrough termination.

► Features & Benefits

Powers up to Two Probes

For Use with P6203, P6204, P6205, P6231, P6243, P6245, P6246, P6247, P6248, P6249, P6330, P6701B, P6703B, P6711, P6713, P5205, P5210, ADA400A and TPC202 on other than TEKPROBE BNC Interfaced Scopes**

Overload Protected

► Applications

High-speed Digital Systems Design

- ECL
- GaAs
- MOS: CMOS; FastCMOS; BiCMOS; TTL

Component Design/Characterization

- Amplitude levels
- Aberrations
- Propagation Delay and Timing
- Bandwidths and Rise Times

Educational Research

Manufacturing Engineering and Test

► Ordering Information

1103

TEKPROBE® Power Supply.

For Use with P6203, P6204, P6205, P6231, P6243, P6245, P6246, P6247, P6248, P6249, P6330, P6701B, P6703B, P6711, P6713, P5205, P5210, ADA400A and TPC202. Powers two probes.

International Power Plugs

Opt. A1 – Opt. A5 – Available. See General Customer Information pages for additional description.

CE



Tektronix measurement products are manufactured in ISO registered facilities.