
# Advanced Antennas

AA-MWH-2640G-B | Antenna, Standard Gain Horn, Passive, Directional



### **Description**

The AA-MWH-2640G-B Standard Gain Horn is a WR-28 waveguide based Ka band antenna featuring high gain and stable beamwidth across its frequency range.

The AA-MWH-2640G-B is based on the standard WR-28 waveguide and features a detachable UG-599/U flange mount which allows for the horn flare and coax-to-waveguide adapter to be used separately.

Each AA-MWH-2640G-B comes standard with NIST Traceable 1m gain and antenna factor calibration data.

### Specifications Electrical

Frequency Range: 26.5GHz – 40GHz Polarization: Linear, Vertical VSWR: < 1.3:1 Typical 3dB Beamwidth: 14° - 17° Typical Horizontal 14° - 20° Typical Vertical Impedance: 50Ω, Nominal Gain: 17-21 dBi Nominal Connector: Type 'K' (EM-7104 | 26.5GHz-40GHz) Wavequide: WR28

### **Mechanical**

Dimensions: Overall Length: 7.2 cm (2.8") Width: 4.3 cm (0.7") Height: 2.7 cm (1.2")


Weight: 45g (0.10 lbs.)

### Mounting Options Available:

**EM-7104** <sup>1</sup>⁄<sub>4</sub> - 20 Vertical/Horizontal mount **EM-7104A** WR-28 Coax-to-waveguide Adapter.


EM-7104B WR-28 20dBi Gain Horn Flare






\*Maximum Gain determined from scans at all radiation angles and elevations. Data shown is typical, not guaranteed.








Data shown is typical, not guaranteed.

#### **Advanced Antennas**






Scale: 6dB/Division.

Data shown is typical, not guaranteed.

#### Advanced Antennas






Scale: 6dB/Division.

Data shown is typical, not guaranteed.

#### **Advanced Antennas**






Scale: 6dB/Division.

Data shown is typical, not guaranteed.






Scale: 6dB/Division.

Data shown is typical, not guaranteed.

#### Advanced Antennas






Scale: 6dB/Division.

Data shown is typical, not guaranteed.

### **Advanced Antennas**






Scale: 6dB/Division.

Data shown is typical, not guaranteed.

#### Advanced Antennas






Scale: 6dB/Division.

Data shown is typical, not guaranteed.

### **Advanced Antennas**






Scale: 6dB/Division.

Data shown is typical, not guaranteed.

#### **Advanced Antennas**






Scale: 6dB/Division.

Data shown is typical, not guaranteed.

### **Advanced Antennas**






Scale: 6dB/Division.

Data shown is typical, not guaranteed.

### **Advanced Antennas**






Scale: 6dB/Division.

Data shown is typical, not guaranteed.

### **Advanced Antennas**






Scale: 6dB/Division.

Data shown is typical, not guaranteed.






Scale: 6dB/Division.

Data shown is typical, not guaranteed.

#### Advanced Antennas





Scale: 6dB/Division.

Data shown is typical, not guaranteed.

### **Advanced Antennas**